

## Specification

Model		PD-122001					PD-122002				
		A0	A1	A2	A3	A0M1	A0	A1	A2	A3	A0M1
<b>Power Rating</b>	<b>20A (Derated to 16A) 120VAC</b>	YES	YES	YES	YES	YES	YES	YES	YES	YES	YES
<b>AC Outlet NEMA 5-20R</b>	<b>Front</b>	4	4	4	4	4	4	4	4	4	4
	<b>Rear</b>	8	8	8	8	8	8	8	8	8	8
<b>Circuit Breaker</b>		YES	YES	YES	YES	YES	YES	YES	YES	YES	YES
<b>Surge Protection</b>	<b>L-N</b>	-	YES	-	-	-	-	YES	-	-	-
	<b>L-N-G</b>	-	-	YES	-	-	-	-	YES	-	-
	<b>L-N-G + Noise Filter</b>	-	-	-	YES	-	-	-	-	YES	-
<b>Indicator</b>	<b>Power-Red</b>	YES	YES	YES	YES	YES	YES	YES	YES	YES	YES
	<b>Surge-Green</b>	-	YES	YES	YES	-	-	YES	YES	YES	-
<b>Power Cord 12AWG</b>	<b>5-20P (01)</b>	YES	YES	YES	YES	YES	-	-	-	-	-
	<b>L5-20P (02)</b>	-	-	-	-	-	YES	YES	YES	YES	YES
<b>Amp Meter</b>		-	-	-	-	YES	-	-	-	-	YES