

Ahoku Electronic Company 5F, No.88, Sec.1, Nei-Hu Rd., Taipei, Taiwan Tel:+886-2-2799-1199 Fax:+886-2-2799-9099

Specification

Model No.	PIR Sensor
Power Supply	3*AAA(4.5V) battery
Frequency	2.4GHz
Modulation	GFSK
Data Rate	250Kbps
Distance	80M open space
Working Temperature	0°C~45°C
Max TX. Power	+4.5 dBm
Sensitivity	-97 dBm
Channel	8 Channel
Freq. Shift	1MHz
RF Current Consumption (Normal)	4mA
RF Current Consumption (Suspend)	60uA
Hight	6.6cm